




Questions?

For customer service please call us at 1-888-743-5766
Office Hours: 8:00 a.m. – 5:00 p.m. PST Monday-Friday



5"-6" LED
Downlight Retrofit Fixture

PLEASE REVIEW THE INSTRUCTIONS AND WARNINGS LISTED BELOW PRIOR TO PROPER INSTALLATION

WARNINGS	CAUTIONS
<ul style="list-style-type: none"> • Risk of fire / electrical shock • LED Downlight installation requires knowledge of luminaire electrical systems. • Risk of electric shock – disconnect power at source before installation • Do not make or alter any open holes in an enclosure of wiring or electrical components during installation. • If fixture or luminaire exhibits abnormal operation (buzzing, flickering, minimal light, etc.), turn off power, remove fixture and contact us. For more information please visit www.eurilighting.com or call our toll-free number 1-888-743-5766. 	<ul style="list-style-type: none"> • Do not look directly at the operating LED Downlight • Do not touch this product with wet hands. • Do not disassemble, repair or alter fixture. • Designed for indoor applications only. • Suitable for Dry, Damp or Wet locations. • The luminaires shall be grounded. • Be careful not to touch the fixture pins to the metal housing when installing. • This Device is not intended for use with emergency exits or emergency lights.

LED DOWNLIGHT INSTALLATION INSTRUCTIONS

<p>1</p>	<p>2</p>	<p>3</p>
<p>Remove your new LED Downlight from its package and verify if the mounting clips are firmly attached. Content should include: (1) Retrofit Kit (can, downlight, and mounting clips) and (1) E26 Base Adapter.</p>	<p>Prior to the installation process, please make sure to TURN OFF all power switches.</p>	<p>Please remove existing can (lamp container) and light bulb to reveal existing socket. If you are replacing a similar fixture please unscrew the existing downlight to reveal socket.</p>
<p>4</p>	<p>5a</p>	<p>5b</p>
<p>Screw-in Euri Lighting E26 Base Adapter into the socket.</p>	<p>Plug-in the end of the E26 base adapter into the female connector of the LED downlight.</p>	<p>For 5" recessed housing please rotate all three mounting clips counter clock. Otherwise keep mounting clips fully extended for 6" recessed housing.</p>
<p>5c</p>	<p>5d</p>	
<p>Push-in the LED Downlight until it has properly touch the surface/ceiling.</p>	<p>Rotate the fixture slightly to ensure the trim is flushed against the ceiling.</p>	